

## FT-7815 JUMPER SETTING

- JP1 : PANEL RESOLUTION SELECT**

Pin 7-8	Pin 5-6	Pin 3-4	Pin 1-2	Panel Type
Short	Short	Open	Short	1024x768 (Single 24bits)
Short	Short	Short	Open	1024x768 (Single 18bits)

- JLVDS\_SEL1 : LVDS VOLTAGE SELECT**

Pin 1-2 Short : 3.3V (for 15" Panel)

Pin 2-3 Short : 5V

- JP2 : TOUCH SOUNDS SELECT**

Pin 1-2 Short : Normal USB Used

Pin 2-3 Short : for Resistive touch sounds used

- JCR\_SEL1 : For CR open/close status port selection**

Pin 1-2 Short : for COM1

Pin 2-3 Short: for COM5

- JCOM\_SEL1 : COM1/COM2 Pin1 connected Setting**

Pin 1-3 Short : COM1 Pin1 connected to 12V

Pin 3-5 Short : COM1 Pin1 connected to DCD

Pin 2-4 Short : COM2 Pin1 connected to 12V

Pin 4-6 Short : COM2 Pin1 connected to DCD

- JCOM\_SEL2 : COM3/COM4 Pin1 connected Setting**

Pin 1-3 Short : COM3 Pin1 connected to 12V

Pin 3-5 Short : COM3 Pin1 connected to DCD

Pin 2-4 Short : COM4 Pin1 connected to 12V

Pin 4-6 Short : COM4 Pin1 connected to DCD

- SW1 : Clear CMOS Setting**

DIP	Switch select	
1 & 2	1: ON, 2: ON	Reserved
	1: ON, 2: OFF	Normal Operation
	1: OFF, 2: ON	Clear CMOS
	1: OFF, 2: OFF	Reserved
3	8: ON	Disable Flash Descriptor Security (override)
	8: OFF	Enable security measures defined in the Flash Descriptor

- COM1~COM4 +5V through BIOS ; VGA +12V through BIOS**

Press Esc to access Advanced\PCH-IO Configuration\

VGA DSUB 12V : Disabled

COM1 DB9 5V : Disabled

COM2 DB9 5V : Disabled

COM3 DB9 5V : Disabled

COM4 DB9 5V : Disabled

