

HC-1521 JUMPER SETTING

- **JP1 : Handset HP/Mic Disable Select**
 - Pin 1-2 Short: No use handset Function
 - Pin 2-3 Short: Use Handset Function
- **JLVDS_SEL : Select LCD Power**
 - Pin 1-3 、 2-4 Short : For Single LVDS
 - Pin 3-5 、 4-6 Short : For Dual LVDS
- **JCOM_SEL1 : COM1/COM2 PORT DC SUPPLY SELECT**
 - Pin 1-3 Short : COM1 Pin1 connected as 12V DC
 - Pin 3-5 Short : COM1 Pin1 connected as DCD
 - Pin 2-4 Short : COM2 Pin1 connected as 12V DC
 - Pin 4-6 Short : COM2 Pin1 connected as DCD
- **JCOM_SEL2 : COM3/COM4 PORT DC SUPPLY SELECT**
 - Pin 1-3 Short : COM3 Pin1 connected to 12V
 - Pin 3-5 Short : COM3 Pin1 connected to DCD
 - Pin 2-4 Short : COM4 Pin1 connected to 12V
 - Pin 4-6 Short : COM4 Pin1 connected to DCD
- **JCOM_SEL3 : COM1/COM2 PORT DC SUPPLY SELECT**
 - Pin 1-3 Short : COM1 Pin9 connected as 5V DC (By BIOS setting)
 - Pin 3-5 Short : COM1 Pin9 connected as RI
 - Pin 2-4 Short : COM2 Pin9 connected as 5V DC (By BIOS setting)
 - Pin 4-6 Short : COM2 Pin9 connected as RI
- **JCOM_SEL4 : COM3/COM4 PORT DC SUPPLY SELECT**
 - Pin 1-3 Short : COM3 Pin9 connected as 5V DC (By BIOS setting)
 - Pin 3-5 Short : COM3 Pin9 connected as RI
 - Pin 2-4 Short : COM4 Pin9 connected as 5V DC (By BIOS setting)
 - Pin 4-6 Short : COM4 Pin9 connected as RI
- **COM1~COM4 : +5V through BIOS ; VGA +12V through BIOS**
 - Press F2 to access Chipset/PCH-IO Configuration
 - VGA DSUB 12V : Disabled
 - COM1 DB9 5V : Disabled
 - COM2 DB9 5V : Disabled
 - COM3 DB9 5V : Disabled
 - COM4 DB9 5V : Disabled

• **SW1 : Clear CMOS & Update vPRO BIOS**

DIP	Switch select	
1 & 2	1: ON, 2: ON	Reserved
	1: ON, : OFF	Normal Operation
	1: OFF, 2: ON	Clear CMOS
	1: OFF, 2: OFF	Reserved
3	3: ON	Disable Flash Descriptor Security (override)
	3: OFF	Enable security measures defined in the Flash Descriptor

