

TX-2300 G2/TX-2300E G2 JUMPER SETTING

Ver. A1

- **JP3 : COM1/COM2 12V DC SUPPLY SELECT**
 Pin 1-3 Short : COM1 Pin1 connected to 12V
 Pin 3-5 Short : COM1 Pin1 connected to DCD
 Pin 2-4 Short : COM2 Pin1 connected to 12V
 Pin 4-6 Short : COM2 Pin1 connected to DCD
- **JP4 : COM3 12V DC SUPPLY SELECT**
 Pin 1-2 Short : COM3 Pin1 connected to 12V
 Pin 2-3 Short : COM3 Pin1 connected to DCD
- **JP5 : COM4 12V DC SUPPLY SELECT**
 Pin 1-2 Short : COM4 Pin1 connected to 12V
 Pin 2-3 Short : COM4 Pin1 connected to DCD
- **JP1 : COM5/COM6 5V DC SUPPLY SELECT (TX-2300E G2 only)**
 Pin 1-3 Short : COM5 Pin9 connected to 5V DC (By BIOS setting)
 Pin 3-5 Short : COM5 Pin9 connected as RI
 Pin 2-4 Short : COM6 Pin9 connected to 5V DC (By BIOS setting)
 Pin 4-6 Short : COM6 Pin9 connected as RI
- **JP2 : For CR open/close status port selection**
 Pin 1-3 、 2-4 Short: For COM1
 Pin 3-5 、 4-6 Short : For COM5

- **SW1 : Clear CMOS Setting**

DIP	Switch select	
1 & 2	1: ON, 2: ON	Reserved
	1: ON, : OFF	Normal Operation
	1: OFF, 2: ON	Clear CMOS
	1: OFF, 2: OFF	Reserved
3	OFF	Reserved

- **COM1~COM6 : +5V through BIOS ; VGA +12V through BIOS**
 Press ESC to access Configuration / Super IO Configuration /OEM IO Configuration
 VGA DSUB 12V : Disabled
 COM1 DB9 5V : Disabled
 COM2 DB9 5V : Disabled
 COM3 DB9 5V : Disabled
 COM4 DB9 5V : Disabled
 COM5 DB9 5V : Disabled (TX-2300E G2 only)
 COM6 DB9 5V : Disabled (TX-2300E G2 only)

